

# 1/2 HP AC CHAIN DRIVE WIFI® GARAGE DOOR OPENER

A COMPLETE, RELIABLE SOLUTION WITH POWERFUL PERFORMANCE.



## KEY FEATURES

**VALUE**  
Package

**CONSISTENT &  
DEPENDABLE**  
Operation

**WIFI**  
Built In

SMART  
SECURE  
RELIABLE

**1/2 HP AC MOTOR** IS PURPOSEFULLY DESIGNED AND BUILT TO LAST.

**CHAIN DRIVE SYSTEM** FOR STEADY PERFORMANCE AND INDUSTRIAL STRENGTH.

**WARRANTY** LIFETIME MOTOR, 1-YEAR PARTS.

**SECURITY+ 2.0®** SAFEGUARDS GARAGE ACCESS BY SENDING A NEW CODE WITH EVERY CLICK.

**POSILOCK®** ELECTRONICALLY PROTECTS AGAINST FORCED OPENINGS.

**ALERT-2-CLOSE** SIGNALS WHEN A DOOR IS BEING CLOSED BY MyQ®.

**THE PROTECTOR SYSTEM®** INVISIBLE LIGHT BEAM AUTO-REVERSES THE DOOR IF THERE IS AN OBSTRUCTION.

**BUILT-IN WI-FI** FOR THE EASIEST WAY TO CONNECT THE GARAGE.

**MyQ TECHNOLOGY** ALLOWS USERS TO KNOW THEIR HOME IS SECURE.

**REAL-TIME ALERTS** INDICATE THE STATUS OF THE GARAGE DOOR VIA EMAIL OR PUSH NOTIFICATIONS.

**MONITOR AND CONTROL** THE OPENER FROM ANYWHERE USING MOBILE DEVICES.

## INCLUDED ACCESSORIES:

### Wireless Keyless Entry

Provides convenient, secure access from outside the garage with a 4-digit PIN.



2220166

877MGX

### Multi-Function Control Panel

Turns on garage door opener lights from inside the garage.



6080960

882RGDW

### (2) 3-Button Remote Controls

Operate up to 3 openers or MyQ Light Accessories each.



2220178

893RGX

## POWERFUL ADD-ONS:

### Mini Universal Remote Control

Compact and portable to provide quick, easy garage access.



2220185

374UT

### Remote Light Control

Enables home lighting control through a garage remote or a smartphone.



2220174

825LM

### MyQ Remote LED Light

Operates automatically with the opener and works with the MyQ app.



6081024

827RGD

## MASTERFUL ENGINEERING.

### MOTOR

- ½ Horsepower
- 1,625 RPM
- Automatic Thermal Protection
- Permanent Lubrication

### POWER

- 120V AC
- 60 Hz Voltage
- 2.7A Current Rating
- UL Listed
- 4' Power Cord (3-Prong)

### MECHANICS

- **Steel Chassis, T-Rail and Trolley**
- **Full Chain Drive Mechanism** (16:1 Gear Reduction and Adjustable Door Arm)
- **Auto-Force** Adjustment for Changing Weather and Environmental Conditions
- **Electronic Limits** for Easy Setup
- **AC WiFi Logic Board** with Built-In Surge Suppressor



### DIMENSIONS

Rail Options	7'	8'	10'
Installed Length	128"	140"	164"
Max. Opening	7'6"	10'	10'

Headroom Clearance Required: 2"

7"

Per second for door to move upward

### SPEED

7"

Per second for door to move downward

## STANDARD SPECS.

## SECURITY

### RADIO CONTROLS

Operating Range: ~200'

Operating Temperature: -35°F to 150°F

### SECURITY +2.0\*

- (2) 3-Button remote controls and wireless keyless entry
- Remote Controls: 310, 315 and 390 MHz Tri-Band\*
- Keyless Entry: 310, 315 and 390 MHz Tri-Band\*
- Garage Door Opener: Frequency Agile on 310, 315 and 390 MHz
- Anti-Burglary Coding


\*Tri-Band on Security+ 2.0 coding only.

### ENCRYPTED CONTROLS

- Multi-Function Control Panel\*
- Program Remote Controls
- Maintenance Alert System
- Easy WiFi Setup

## SMART

### MyQ® RADIO



50-Channel FHSS

(Frequency Hopping Spread Spectrum)

- Provides 2-way communication from garage door opener and MyQ Accessories.
- Enables monitoring and control of garage door openers and lighting controls via smartphone, tablet or computer.

### HOMELINK® COMPATIBLE (VERSION 4.0 OR HIGHER\*)

\*May require an external adapter depending on the model and year of your vehicle. Visit HomeLink.com for additional information.

## ELECTRICAL

### LIGHTING



- Max. 2 100-Watt Light Bulbs
- Solid-State Light Delay
- Adjustable Time
- Enhanced CFL (Compact Fluorescent) Compatible, Max. 26 Watts

## SHIPPING.

### SHIPPING WEIGHT (in lbs.)



### CARTONS (2)

CARTON 1: 20" x 12" x 10"

- Garage Door Opener Head
- Multi-Function Control Panel
- (2) 3-Button Remote Controls
- Wireless Keyless Entry
- The Protector System® Safety Reversing Sensors

CARTON 2: 10'4" x 5" x 5" (for 7' Rail)

- Assembled Solid-Steel Chain T-Rail

## CONVENIENCE AND SAFETY.

- Alert-2-Close/Unattended Close Operation (with Select Accessories)\*
- Emergency/Quick Release
- Automatic Trolley Reconnect
- Ventilation/Pet Opening
- Down Safety Reverse
- Up Safety Stop
- Safety Beam obstruction Turns Lights On
- Maintenance Alert System
- Garage Door Opener Capacity of up to 24 Remote Controls, 2 Wireless Keyless Entry Systems and 16 MyQ Devices



HomeLink® and the HomeLink House® logo are registered trademarks of Gentex Corporation

\*: To reduce the risk of injury to persons, only use alert-2-Close/Unattended Close Operation features when installed with a sectional door.